



### Box Properties

--Description--

Name:

Type: Shape: --Box Parameters--

Fill =

### Driver Properties

--Description--

Name: AF.15 REX FUSION 1350W 4 OHMS

Type: Standard one-way driver

--Configuration--

**No. of Drivers = 1**

--Mechanical Parameters--

Fs = 58,85 Hz

Qms = 17,41

Vas = 47,38 liters

Cms = 0,0456 mm/N

Mms = 160,3 g

Rms = 3,407 kg/s

Xmax = 6, mm

Xmech = 9, mm

P-Dia = 330, mm

Sd = 855,3 sq.cm

P-Vd = 0,513 liters

--Electrical Parameters--

Qes = 0,51

Re = 3,3 ohms

Le = 0,713 mH

Z = 3,96 ohms

BL = 19,58 Tm

Pe = 1350 watts

--Electromech. Parameters--

Qts = 0,495

no = 1,826 %

1-W SPL = 94,81 dB

2.83-V SPL = 98,66 dB