


By teste, teste



Box Properties

--Description--

Name:

Type: Shape: --Box Parameters--

Fill =

Driver Properties

--Description--

Name: AF. 18 REX FUSION 1350W 4 OHMS

Type: Standard one-way driver

--Configuration--

No. of Drivers = 1

--Mechanical Parameters--

Fs = 43,27 Hz

Qms = 24,1

Vas = 69,19 liters

Cms = 0,0666 mm/N

Mms = 203,2 g

Rms = 2,292 kg/s

Xmax = 6, mm

Xmech = 9, mm

P-Dia = 330, mm

Sd = 855,3 sq.cm

P-Vd = 0,513 liters

--Electrical Parameters--

Qes = 0,47

Re = 3,3 ohms

Le = 0,691 mH

Z = 3,96 ohms

BL = 19,7 Tm

Pe = 1350 watts

--Electromech. Parameters--

Qts = 0,461

no = 1,15 %

1-W SPL = 92,81 dB

2.83-V SPL = 96,65 dB