



### Box Properties

--Description--

Name:

Type: Shape: --Box Parameters--

Fill =

### Driver Properties

--Description--

Name: AF 18 REX FUSION 950W 4 OHMS

Type: Standard one-way driver

--Configuration--

**No. of Drivers = 1**

--Mechanical Parameters--

Fs = 46,51 Hz

Qms = 26,68

Vas = 131,7 liters

Cms = 0,0587 mm/N

Mms = 199,5 g

Rms = 2,185 kg/s

Xmax = 6, mm

Xmech = 9, mm

P-Dia = 400, mm

• Sd = 1257 sq.cm

P-Vd = 0,754 liters

--Electrical Parameters--

Qes = 0,71

Re = 3,4 ohms

Le = 0,787 mH

Z = 4,08 ohms

BL = 16,71 Tm

Pe = 950, watts

--Electromech. Parameters--

Qfs = 0,692

no = 1,799 %

1-W SPL = 94,75 dB

2.83-V SPL = 98,47 dB